

Battery Pack Setup & Installation

Before using your battery packs for the first time, fully charge each battery using the provided charger. Plug the battery into the charger and allow it to charge completely. The charger indicator light will turn green when the battery has reached a full charge.

To secure the battery pack to the frame, position it next to the Illumipeak control housing along the truss bar. Wrap the attached Velcro flap around the truss bar and press firmly to ensure a tight and secure hold.

After the battery is securely mounted, connect the battery power cord to the input port on the Illumipeak control housing. Ensure the connection is fully inserted and secure before powering on the system.



Dual Peak Kit Setup

If you have a dual peak kit, begin by identifying the primary peak pole, which is the pole connected to your main power source. Locate the provided connection cable and insert one end into the input port on the primary peak pole. Then connect the other end of the cable into the input port on the second peak pole to supply power to both units.

Once connected, both peak poles will receive power, and each peak can be operated and dimmed independently using its own control housing dimmer dials.

